


Straight Coupling VS8010 Series



Standard Material
From Stock

PRODUCT ID	DESCRIPTION	D1	D2	L1	S1	S3	S4	Standard Material From Stock			
								S	FG	SS	B
VS8010-L06	Straight Coupling	6	6	30	11	12	12	•			
VS8010-L08	Straight Coupling	8	8	35	12	14	14	•			
VS8010-L08-06	Straight Coupling	8	6	40.5	12	14	12	•			
VS8010-L10	Straight Coupling	10	10	42	17	19	19	•			
VS8010-L10-06	Straight Coupling	10	6	41.5	17	19	12	•			
VS8010-L10-08	Straight Coupling	10	8	42	17	19	14	•			
VS8010-L12	Straight Coupling	12	12	43	19	22	22	•			
VS8010-L12-06	Straight Coupling	12	6	42	19	22	14	•			
VS8010-L12-08	Straight Coupling	12	8	42.5	19	22	17	•			
VS8010-L12-10	Straight Coupling	12	10	43.5	19	22	19	•			
VS8010-L15	Straight Coupling	15	15	46	24	27	27	•			
VS8010-L15-10	Straight Coupling	15	10	45	24	27	19	•			
VS8010-L15-12	Straight Coupling	15	12	44.5	24	27	22	•			
VS8010-L18	Straight Coupling	18	18	48	27	32	32	•			
VS8010-L18-10	Straight Coupling	18	10	47	27	32	19	•			
VS8010-L18-12	Straight Coupling	18	12	46.5	27	32	22	•			
VS8010-L18-15	Straight Coupling	18	15	48	27	32	27	•			
VS8010-L22	Straight Coupling	22	22	52	32	36	36	•			
VS8010-L22-12	Straight Coupling	22	12	48.5	32	36	22	•			
VS8010-L22-15	Straight Coupling	22	15	50	32	36	27	•			
VS8010-L22-18	Straight Coupling	22	18	51	32	36	32	•			
VS8010-L28	Straight Coupling	28	28	54	41	41	41	•			
VS8010-L28-18	Straight Coupling	28	18	52	41	41	32	•			
VS8010-L28-22	Straight Coupling	28	22	41	41	41	36	•			
VS8010-L35	Straight Coupling	35	36	63	46	50	50	•			
VS8010-L35-22	Straight Coupling	35	22	59	46	50	36	•			
VS8010-L35-28	Straight Coupling	35	28	59	46	50	41	•			
VS8010-L42	Straight Coupling	42	42	66	55	60	60	•			
VS8010-S06	Straight Coupling	6	6	45	14	17	17	•			
VS8010-S08	Straight Coupling	8	8	47	17	19	19	•			
VS8010-S08-06	Straight Coupling	8	6	48	17	19	17	•			
VS8010-S10	Straight Coupling	10	10	49	19	22	22	•			
VS8010-S10-06	Straight Coupling	10	6	48.5	19	22	17	•			
VS8010-S10-08	Straight Coupling	10	8	48.5	19	22	19	•			
VS8010-S12	Straight Coupling	12	12	51	22	24	24	•			
VS8010-S12-06	Straight Coupling	12	6	50.5	22	24	17	•			
VS8010-S12-08	Straight Coupling	12	8	50.5	22	24	19	•			
VS8010-S12-10	Straight Coupling	12	10	51	22	24	22	•			
VS8010-S14	Straight Coupling	14	14	57	24	27	27	•			
VS8010-S14-10	Straight Coupling	14	10	54.5	24	27	22	•			
VS8010-S14-12	Straight Coupling	14	12	54.6	24	27	24	•			
VS8010-S16	Straight Coupling	17	16	57	27	30	30	•			
VS8010-S16-12	Straight Coupling	17	12	54.6	27	30	24	•			
VS8010-S16-14	Straight Coupling	17	14	58	27	30	27	•			
VS8010-S20	Straight Coupling	20	20	66	32	36	36	•			
VS8010-S20-10	Straight Coupling	20	10	56.5	32	36	22	•			
VS8010-S20-12	Straight Coupling	20	12	56.5	32	36	24	•			
VS8010-S20-16	Straight Coupling	20	16	60	32	36	30	•			
VS8010-S25	Straight Coupling	25	25	74	41	46	46	•			
VS8010-S25-16	Straight Coupling	25	16	68	41	46	30	•			
VS8010-S25-20	Straight Coupling	25	20	68	41	46	36	•			
VS8010-S30	Straight Coupling	30	30	80	46	50	50	•			
VS8010-S30-20	Straight Coupling	30	20	71	46	50	36	•			
VS8010-S30-25	Straight Coupling	30	25	77	46	50	46	•			
VS8010-S38	Straight Coupling	38	38	90	55	60	60	•			
VS8010-S38-30	Straight Coupling	38	30	87	55	60	50	•			